

Designed by Louis Weisdorf

PRODUCT



COLORS



DESCRIPTION

The Multi-Lite was first drawn in 1972 when Louis Weisdorf did an exception to his own design custom of using multiple repeating elements. Instead it reflects his passion for diversity.

The Multi-Lite pendant has two individual rotating shades and can be transformed into multiple combinations where the light can be directed upwards, downwards or exude an assymetrical art light. The lamp is available in seven colors and all the shades are white lacquered inside.

VERSION - MULTI-LITE S PENDANT

Colour codes are indicative:

All Brass - brass colored cable

Brass/Charcoal Black - RAL 9011 - Gloss level 5 - black cable

Brass/White - RAL 9003 - Gloss level 15 - white cable

Brass/Blue - RAL 250 50 25 - Gloss level 15 - brass colored cable


All Chrome - black cable

Chrome/Black - RAL 9005 - Gloss level 15 - black cable Chrome/White - RAL 9003 - Gloss level 15 - white cable

Canopy:

- Brass on brass versions
- Chrome on chrome versions

MEASUREMENTS



FACTS

 ${\sf MEASUREMENT} - Lx\,Wx\,H\,mm$ Lamp height: 360 mm Lamp diameter: Ø360 mm Canopy size: Ø115 x 57 mm Wire length, exposed: Approx.. 4000 mm

WEIGHT ITEM - LAMP INCL. WIRE 2200 G

PACKAGING TYPE Cardboard box

PACKAGING MEASUREMENT - Lx Wx Hcm

L: 38 x W: 38 x H: 51 cm

 $WEIGHT\ PACKAGING\ -\textit{MATERIAL\ TYPE\ (recycleable)}$

- Polystyrene: 272 g PE polybag: 25 g
- Cardboard inside: 396 g - Cardboard outside: 1120 g

WEIGHT PACKAGING - TOTAL

NUMBER OF PARCELS

1 pcs.



Designed by Louis Weisdorf

ACCESSORIES

ENVIRONMENT

-

TESTS

CERTIFICATION AND LABELS


CE-certified


SAFETY INSTRUCTIONS

If the cord or other electrical part is damaged, switch of the lamp and do not use it until it is repaired by a qualified electrician.

INSTALLATION INSTRUCTIONS

Instructions document no. 58-20-001-01





LIGHT SOURCE:

- Socket: E27 base
- Bulb types recommended:



- Recommended light sources:

Halogen light bulb

- Recommended wattage: 46 W
- Max wattage: 57 W

All fluorescens light bulbs

- Recommended wattage: 15 W
- Max wattage: 18 W

LED retrofit light bulbs

- Recommended wattage: 9,5 W
- Max wattage: 11,5 W
- Max. light out put for above lamps: 1050 Lumens ≈ (75 WATT incandescent bulbs)
- All lamps can be fitted with a din Please contact your local electrician.
- Lightbulb not included

*Euro voltage: 230 V

- *Frequency: 50 Hz
- *Supply voltage: AC power ~
- *Normally Closed: IP20





Class II / Double insulated



Luminaires accepted for mounting on a flammable base